

## **STRONG 4650 SATELLITE RECEIVER**

### **Scanning the new transponder 12546 for 3ABN**

Switch on the satellite receiver and TV as you normally would to watch one of the channels.

To scan in 3ABN:

- From the MAIN MENU highlight INSTALLATION and press OK. The receiver may request a password. Enter 0000 or try 9402
- Scroll down and highlight MANUAL SCAN and press OK
- Press the GREEN (AUDIO) button on the remote
- Highlight FREQUENCY and enter 12546 by using the numbers on the remote
- Make sure the SYMBOL RATE is 22500 (If not change it using the numbers on the remote)
- Make sure POLARIZATION is V (if not scroll left or right using the remote and select V)
- Highlight SEARCH TYPE and scroll left or right and select FTA ONLY
- Highlight NETWORK SEARCH and scroll left or right and select OFF
- Please check the above setting before continuing
- Next press the OK button and the receiver will begin searching for the channels
- Once the scan has finished press the EXIT button until back to main screen
- Scan through the channels using the up and down channel buttons and search for 3ABN

NEW HOME. This is the new 3ABN channel position. Write down the channel number so you can get to 3ABN easily.

OR

### **CHANGE THE POSITION OF THE NEW 3ABN CHANNEL**

- From the MAIN MENU scroll UP highlight MOVE CHANNELS and press the OK button.
- Next scroll through the channel list to find 3ABN NEW HOME and highlight it
- Press the OK button and scroll UP or DOWN and move it to where you would like it to appear in the list then press OK.
- Once you are finished press the EXIT button on the remote and the receiver will display a message "Settings were changed DO YOU WANT TO SAVE?"
- Highlight YES in yellow and press the OK button.
- Now press the EXIT button twice
- You can then delete the old 3ABN Channel if you wish
- 

Watch 3ABN on this new channel from now on. When the old channel goes off air the old channel slot will be vacant.